# VFAT Temperature Monitoring on an ME0 GEM Module



Erick Yanes and Marcus Hohlmann (on behalf of the CMS Muon Group) Florida Institute of Technology, Melbourne, FL

October 23<sup>rd</sup>, 2025

SESAPS 2025 James Madison University, Harrisonburg, VA









#### LHC, CMS, and ME0



- The Large Hadron Collider (LHC) is a pp collider running at  $E_{CM} = 13.6 \text{TeV}$
- With the High Luminosity (HL) upgrade, the luminosity with increase by half an order of magnitude
- More data will be obtained to investigate exotic physics processes
- The Compact Muon Solenoid (CMS) is one of the detectors being upgraded
- · Existing electronics are being upgraded, and three new Gas Electron Multiplier (GEM) detectors are being installed
  - GE1/1 Currently installed for RUN 3
  - GE2/1 Early Production Phase
  - ME0 Production Phase
- ME0 will track muon paths at the highest  $\eta$
- One ME0 stack is composed of six modules




R-z cross section of CMS including HL-LHC upgrade detectors [1]



#### ME0 Module - Electronics




- Very Forward ATLAS and TOTEM (VFAT) front-end electronics boards Digitize and read-out ionization signal from the read-out strips
  - 128 channels (strips) per VFAT
  - 24 VFATs per module
- OptoHybrid (OH) Collects data from the VFATs and sends to the back-end through optical fibers
  - 2.56 Gbps to Front-end electronics
  - 10.24 Gbps to Back-end electronics
- GEM Electronics Board (GEB) Route connections between the VFATs and OHs




## **Cooling Circuit Temperature Monitor**




- Prototype cooling circuit on ME0
- · Focuses on cooling the OHs
- Does not make contact with all of the VFATs
- Two external temperature sensors
- Ambient temperature and humidity sensor used to calculate dew point
- CW-5200 chiller pumps cold water through the circuit
- Turns on and off to maintain temperature





### **VFAT Temperature Sensors**






- VFATs have two temperature sensors
- Internal temperature sensor inside the ASIC
- External temperature sensor (RT1) on the PCB
- Neither temperature sensor is properly calibrated
  - During VFAT calibration, the internal temperature sensor is not calibrated a priori
  - Constant current source for Rt1 can vary depending on the VFAT or voltage supplied
- Also use a Koolance temperature sensor to crosscheck VFAT recorded temperatures





## **Reading VFAT Temperature Sensors**



- Neither the internal nor external temperature sensors are calibrated
- Internal temperature sensors are all subzero and External temperature sensors range from 4 to 40°C
- However, both temperature sensors respond to changes in temperature correctly
- Just need to provide an offset to the recorded temperature values







#### Main Goal of This Work




How to use the available temperature sensors to calibrate and monitor the VFAT temperatures during normal operations?

## Calibrated Temperature Sensors



- Need a temperature sensor on the chamber that is similar to the VFAT temperatures
- With cooling on, both the VFATs (in SLEEP mode) and the OHs have a similar temperature  $(\sim 26^{\circ} \text{C})$
- Can use an OH to calibrate the VFATs near it.
- Method for calibrating and recording the VFAT temperatures:
  - 1. Turn on cooling and let it reach a minimum temperature (3 minutes)
  - 2 Power on and initialize the frontend
  - 3. Record the temperature of each OH temperature sensor
  - 4. Record the VFAT temperatures
  - 5 Find an offset for each VFAT such that for the first measurement  $OH_{temp} = VFAT_{temp} + Offset$
  - 6. Get the VFATs as close to normal
  - operations as possible (set them to RUN mode, unmask the VFAT channels, etc.) 7. Record VFAT<sub>Temp</sub>+Offset every minute




#### Measured VFATs



- Recorded four different VFATs with the Koolance Temperature Sensor
- Wanted a mix of cooled and uncooled VFATs
- Choose the following VFATs:
  - VFAT8 Cooled by large copper plate
  - VFAT1 Cooled by copper pipe
  - VFAT14 Uncooled
  - VFAT9 Uncooled and surrounded by electronics
- Recorded temperatures with the protective metal cover






### **VFAT Temperature Comparison – VFAT8 & VFAT1**




#### VFAT8

- Expecting to be the coldest, covered by large copper plate
- Cooling circuit does not make contact with this VFAT due to height of cooling circuit bracket
- Koolance sensor averages to 27.5°C
- Internal sensor averages to 30.0°C
- Internal sensor is about +2.5°C off



#### VFAT1

- Expecting to be the 2nd coldest
- · Contacts the copper pipe of the cooling circuit
- About 1°C cooler than VFAT8
- Koolance sensor averages to 26.5°C
- Internal sensor averages to 28.75°C
- About +2.25°C off




## VFAT Temperature Comparison – VFAT14 & VFAT9




#### VFAT14

- Expecting to be the 2nd warmest, no contact with the cooling circuit
- Koolance sensor averages to 33°C
- Internal sensor averages to 33°C
- Near perfect temperature agreement



#### VFAT9

- Expecting to be the warmest, no contact with the cooling circuit and surrounded by electronics
- Koolance sensor averages to 33.5°C
- Internal sensor averages to 31.0°C
- About -2.5°C off



### **VFAT Temperature Comparison – Summary**




- This method works decently well at calibrating the VFATs
- $\bullet$  Able to get within  $\pm 2.5^{\circ} \text{C}$  for these VFATs
- These are expected to be the most extreme temperature differences based on amount of contact with the cooling circuit and surrounding electronics
- All VFATs should be within ±2.5°C as well
- · Moving forwards this method will be used

VFAT #	Internal Sensor (°C)	Koolance Sensor (°C)	Difference (°C)
8	30.0	27.5	+2.5
1	28.75	26.5	+2.25
14	33.0	33.0	0
9	31.0	33.5	-2.5


### Long Term Test



- Performed a 24 hour test
- Temperatures were stable, aside from the chiller cycle
- Noticeable gap between VFATs that make good contact with the cooling circuit and those that don't
- Averaging each VFAT temperature shows coolest VFATs make contact with the copper pipe




## ME0 OH0 Temperatures (°C)




## Cooling "Failure" Test



- Did a simulated "Cooling Failure" test
- Monitored the VFAT temperatures for three hours
- · First hour, cooling is on like normal
- · Afterwards, cooling is turned off
- Narrow GEB gets hotter than the Wide GEB by nearly 3°C
- Most cooled VFATs end up the hottest
- Seems the cooling circuit now retains heat, rather than dissipating it
- $\bullet$  VFATs only reach up to  $\sim 40^{\circ}$  C, would be more concerned about OH temperatures





#### Conclusion



- Using this method, saw that the VFAT's temperature sensor can have an error of  $\pm 2.5^{\circ}$ C
- With longer tests, reading out all VFAT temperatures show:
  - Touching cooling circuit: 29 30°C
  - Not touching the cooling circuit: 32 33°C
- When cooling is turned off, see the most cooled VFATs (Narrow GEB) become the hottest
- $\bullet~$  VFATs only reach up to  ${\sim}40^{\circ}\text{C},$  would be more concerned about the OH temperatures
- Few more tests are planned:
  - Plan to monitor VFAT temperatures on an irradiated chamber
  - Have a large X-Ray box to irradiate the whole chamber at once
  - View if there are changes in temperature when charge enters the VFAT channels
  - · Plan to check this method again with a cooling bracket for the OH
  - · Does not change these results since it would not change the VFAT cooling
  - Would change the calibration, since OHs would be cooler
  - Want to see if this method of calibration is viable for production modules installed in CMS
- We'd like to thank the DOE Office of Science HEP and NSF MREFC program for their support of this work

#### **Questions?**





#### References

[1] The Phase-2 Upgrade of the CMS Muon Detectors.

Technical report, CERN, Geneva, 2017.

This is the final version, approved by the LHCC.



## Backup